

# Wiring the strobe light

## Method 1

- This method is commonly use when the current draw of the strobe and wired devices are low.
- Use a 0.5 mm Ripcord for this connection.
- Connect the RED wire from the strobe to the AUX + on the alarm panel.
- Next connect the BLACK wire from the strobe to the assigned PGM on the alarm panel.
- The PGM will have to be programmed to facilitate this function.
- It might be required in some instances to extend the wire between the strobe and alarm panel. When this is done the extension points must be soldered and properly insulated.

